



Table of Registers ver. 1.0

	Name	Addr	Register Type	Default	Range
00000	Reserved	0x0000	Input		
00001	Operation	0x0001	Input	0x0002	0x0001 Stopped 0x0002 Started 0x0008 Error 0x0080 Restarting
00002	ErrCode	0x0002	Input		
00003	Co2Value	0x0003	Input		
02048	OpSignal	0x0800	Holding	0x0000	0x0000 Ready 0x0001 Stopped 0x0002 Started 0x0008 Error 0x0080 Restarting
65280	AppType	0xFF00	Input	0x0002	
65281	AppID	0xFF01	Input	0x0015	
65282	SWRelease	0xFF02	Input	0x0001	
65283	SWVersion	0xFF03	Input	0x0000	
65284	SWLevel	0xFF04	Input	0x0000	
65285	SWPatch	0xFF05	Input	0x0000	
65286	HWType	0xFF06	Input	0x001A	
65287	CmdReply	0xFF07	Input	0x0000	0x0000 Nothing 0x0002 Programming Done 0x0082 Programming Error 0x0003 Going to Application Mode 0x0083 Can't go to application Mode 0x0004 Going to Boot loader Mode 0x0084 Can't go to boot loader Mode 0x008F Function not Supported
65288	Satus	0xFF08	Input	0x0000	0 or 1
465408	Cmd	0xFF80	Holding	0x0000	0x0000 Nothing / Clear 0x0001 Clear 0x0002 Program Configuration 0x0003 Set Application mode And Reboot 0x0004 Set Boot loader Mode and Reboot 0x0005 Reset Communication to Factory default
465409	Address	0xFF81	Holding	0x0015	1 to F7
465410	Baud Rate	0xFF82	Holding	0x0003	0x0001 9600 0x0002 19200 0x0003 115200 0x0081 300 0x0082 1200 0x0083 4800 0x0084 38400
465411	Stop Bits	0xFF83	Holding	0x0001	0x0001 1 Bit 0x0002 2 Bit
465412	Parity	0xFF84	Holding	0x0001	0x0000 None 0x0001 Even 0x0002 Odd